



# 100% Material Declaration Data Sheet for 7 Series FFG1158

PK588 (v1.0) January 25, 2013

**Average Weight: 13.6002g**

Component	Substance Description	CAS Number or Description	Percentage of Component	Use in Product	Component Weight/ Substance Weight (grams)	Component Percent of Total
<b>Silicon Die</b>					<b>0.828955</b>	<b>6.095</b>
	Silicon (Si)	7440-21-3	100.00	Basis	0.828955	
<b>Solder Bump</b>					<b>0.038857</b>	<b>0.286</b>
	Tin (Sn)	7440-31-5	63.00	Basis	0.024480	
	Lead (Pb)	7439-92-1	37.00	Basis	0.014377	
<b>Solder Paste</b>					<b>0.011300</b>	<b>0.083</b>
	Tin (Sn)	7440-31-5	96.50	Basis	0.010905	
	Silver (Ag)	7440-22-4	3.00	Basis	0.000339	
	Copper (Cu)	7440-50-8	0.50	Basis	0.000057	
<b>Capacitor 1</b>					<b>0.041280</b>	<b>0.304</b>
	BaTiO3 type	12047-27-7	70.60	Ceramic	0.029144	
	Nickel (Ni)	7440-02-0	6.70	Inner electrode	0.002766	
	Copper (Cu)	7440-50-8	20.10	Outer electrode	0.008297	
	Nickel (Ni)	7440-02-0	0.80	Plating 1	0.000330	
	Tin (Sn)	7440-31-5	1.80	Plating 2	0.000743	
<b>Capacitor 2</b>					<b>0.015200</b>	<b>0.112</b>
	BaTiO3 type	12047-27-7	61.70	Ceramic	0.009378	
	Nickel (Ni)	7440-02-0	4.89	Inner electrode	0.000743	
	Indium tin oxide	50926-11-9	18.30	Outer electrode	0.002782	
	Copper (Cu)	7440-50-8	13.40	Outer electrode	0.002037	
	Nickel (Ni)	7440-02-0	0.49	Plating 1	0.000074	
	Tin (Sn)	7440-31-5	1.22	Plating 2	0.000185	
<b>Capacitor 3</b>					<b>0.003000</b>	<b>0.022</b>
	BaTiO3 type	12047-27-7	66.00	Ceramic	0.001980	
	Nickel (Ni)	7440-02-0	2.67	Inner electrode	0.000080	
	Copper (Cu)	7440-50-8	23.33	Outer electrode	0.000700	
	Nickel (Ni)	7440-02-0	2.33	Plating 1	0.000070	
	Tin (Sn)	7440-31-5	5.67	Plating 2	0.000170	

© Copyright 2013 Xilinx, Inc. XILINX, the Xilinx logo, Virtex, Spartan, ISE, and other designated brands included herein are trademarks of Xilinx in the United States and other countries. All other trademarks are the property of their respective owners

Component	Substance Description	CAS Number or Description	Percentage of Component	Use in Product	Component Weight/ Substance Weight (grams)	Component Percent of Total
<b>Capacitor 4</b>					<b>0.011160</b>	<b>0.082</b>
	BaTiO3 type	12047-27-7	51.10	Ceramic	0.005703	
	Nickel (Ni)	7440-02-0	27.00	Inner Electrode	0.003013	
	Copper (Cu)	7440-50-8	16.00	Outer Electrode	0.001786	
	Glass	65997-17-3	0.90		0.000100	
	Nickel (Ni)	7440-02-0	2.00	Plating1	0.000223	
	Tin (Sn)	7440-31-5	3.00	Plating2	0.000335	
<b>Underfill</b>					<b>0.082000</b>	<b>0.603</b>
	Bisphenol F/ epichlorohydrin copolymer	9003-36-5	20.00	Basis	0.016400	
	Phenolic Resin	Trade Secret	15.00	Basis	0.012300	
	Bisphenol A type liquid epoxy resin	25068-38-6	5.00	Basis	0.004100	
	Amine type accelerator	Trade Secret	5.00	Basis	0.004100	
	Silicon Dioxide	60676-86-0	51.50	Basis	0.042230	
	Carbon Black	1333-86-4	1.00	Basis	0.000820	
	Additives	Trade Secret	2.50	Additive	0.002050	
<b>Lid</b>					<b>7.290000</b>	<b>53.602</b>
	Copper (Cu)	7440-50-8	99.15	Main Material	7.228035	
	Nickel (Ni)	7440-02-0	0.85	Main Material	0.061965	
<b>Lid Adhesive</b>					<b>0.215000</b>	<b>1.581</b>
	Aluminium Oxide Al2O3	1344-28-1	70.00	Main Material	0.150500	
	Dimethyl siloxane, dimethylvinyl-terminated	68083-19-2	30.00	Main Material	0.064500	
<b>Solder Ball</b>					<b>0.964719</b>	<b>7.093</b>
	Tin (Sn)	7440-31-5	96.50	Main Material	0.930954	
	Silver (Ag)	7440-22-4	3.00	Main Material	0.028942	
	Copper (Cu)	7440-50-8	0.50	Main Material	0.004824	
<b>Substrate</b>					<b>4.098707</b>	<b>30.137</b>
	Copper (Cu)	7440-50-8	43.34		1.776380	
	Tin (Sn)	7440-31-5	1.16		0.047545	
	Lead (Pb)	7439-92-1	0.33		0.013526	
	Silver (Ag)	7440-22-4	0.02		0.000820	
	BT Core	N/A	38.40		1.573903	
	ABF	N/A	14.90		0.610707	
	Solder Mask	N/A	1.85		0.075826	

## Revision History

The following table shows the revision history for this document.

Date	Version	Description of Revisions
01/25/2013	1.0	Initial Xilinx release.

## Notice of Disclaimer

Xilinx regards this materials data to be correct but makes no guarantee as to its accuracy or completeness, including, but not limited to, with respect to its compliance with applicable environmental laws and regulations. Xilinx subcontracts the production, test and assembly of hardware devices to independent third-party vendors and materials suppliers (“Contractors”). All data provided hereunder is based on information received from Contractors. Xilinx has not independently verified the accuracy or completeness of this information which is provided solely for your reference in connection with the use of Xilinx products.